Product Line

CISRACK

Type

RM-CI-T14

Supported Models

MERAKI MX68
MERAKI MX68W
MERAKI MX68CW
MERAKI MX75

DIMENSIONS	1U
COLOR	Metallic Blue
PACKING DIMENSIONS	80 x 520 x 270 mm 3.14 x 20.47 x 10.63 in
PRODUCT DIMENSIONS (height x width x depth)	44 x 482 x 217 mm 1.73 x 18.98 x 8.54 in



MOUNTING INSTRUCTIONS

1. Remove the 4 rubber feet from your Cisco appliance.
2. Remove the 2 bolts (situated on the front side of the appliance) from the bottom of the Cisco appliance.
3. Place your Cisco appliance backwards through the FRONT opening of the rack.
4. Turn over the rack with the Cisco appliance.
5. For **MX68:** Use the original bolts to fix the Cisco appliance on the rack and turn it back over.
   For **MX75:** Use the provided bolts to fix the appliance on the rack and turn it back over.
   Tip: use a table edge so the appliance is pinned down to the frame and the bolt holes line up.
6. Place the power supply on the rack and tie it down with the 2 zip ties.
7. Lead the low voltage power cable through the large square hole towards the front of the rack and connect it to the power inlet.
8. Tie the excess length of the power cable down with the 3rd zip tie.
9. Place the light pipe through the opening of the rack. See picture above.
10. Place your CisRack in your 19 inch rack.

Please ensure proper ventilation according to the network appliance manufacturer guidelines.

PACKAGE CONTENTS

Qty	Description
1	CisRack + light pipe
3	Zip ties
1	Torx T8 key
2	Bolts for MX75

Consider the environment, recycle where applicable.

Rackmount.IT rack mount kits are RoHS compliant, developed & manufactured in the Netherlands and made of first quality parts.

In case of problems please contact your reseller or sales@rackmount.it.

Revision 1 - 12-10-2021

EMEA Office
Nonnenveld 27
4811 HN Breda
The Netherlands
T +31 76 200 37 40
E sales@rackmount.it
WWW.RACKMOUNT.IT

US Office
9201 Metric Blvd - Unit A
Austin - TX 78758
United States
T +1 512 521 03 33
E sales-us@rackmount.it

RACKMOUNT.IT