

Smartvest Wireless Door Bell

Art. no. FUSG35010A

Page 1 of 2



- Smartvest extension for signalling indoors
- Five door bell/signal tones (four door bell tones, one alarm tone), which can be configured individually (i.e. assignment of sensor to door bell tone)
- Volume can be set at three different levels
- Can also be used for signalling in the event of an alarm
- Automatic supervision with functional tests repeated daily and feedback sent to the Smartvest alarm control panel
- Visual feedback via blue LED when starting up and in use
- Low battery notification sent to the Smartvest alarm control panel

The Smartvest Wireless Door Bell is a Smartvest extension for signalling indoors. The door bell supports five different signal tones and can play the signals at three different volumes (four door bell tones, one alarm tone). The triggers for a signal can be individually configured. This means that the Wireless Door Bell is suitable for use as a door bell and a sounder. Automatic supervision (functional tests repeated daily) to the alarm control panel means that you can monitor the door bell's functionality at all times and can react to a low battery in good time.

Smartvest Wireless Door Bell

Art. no. FUSG35010A

Page 2 of 2

Technical Data:

Material	Plastic
Color	White
Power consumption Standby	0,0265 mA
Dimensions	60 x 105 x 28 mm
Display	LED
Battery type	AA 1.5V Alkaline
Width	60 mm
Gross weight	0,19 kg
Adjustable alarm tone	5 Gong-tones
Radio frequency	868 MHz
Housing material	ABS
Battery quantity	3
Height	105 mm
Length	28 mm
Max. battery life	1 year(s)
Max. operating temperature	40 °C

Max. humidity	80 %
Max. receiving range (outdoors)	100 m
Max. receiving range (building)	30 m
Max. sending range (outdoors)	100 m
Max. sending range (building)	30 m
Min. operating temperature	-10 °C
Modulation	FSK
Net weight	0,145 kg
Tamper monitoring	no
Sound pressure	max. 80 dba dB
IP protection class	20
Power consumption	265 mA
Environmental class	2