Product Line

**FB-RACK**

Type

**RM-FB-T3**

## Supported Models

**AVM FRITZ!BOX 6660 CABLE**
**AVM FRITZ!BOX 6890**
**AVM FRITZ!BOX 6890 LTE V2**
**AVM FRITZ!BOX 7590**

| | |
|---|---|
| DIMENSIONS | 1.3U |
| COLOR | RAL 9003 White |
| PACKING DIMENSIONS | 80 x 520 x 270 mm<br>3.14 x 20.47 x 10.63 in |
| PRODUCT DIMENSIONS (height x width x depth) | 57 x 482 x 217 mm<br>2.24 x 18.98 x 8.54 in |



# MOUNTING INSTRUCTIONS



1. Optional for 6890 LTE v2: Remove the metal circles with a screwdriver and a hammer and connect the pigtails from the back of the FRITZ!Box to the round holes. Pigtails not provided.
2. Place the FRITZ!Box from the back through the opening of the rack.
3. Connect the power cable to the FRITZ!Box and secure the cable with the zip tie on the rack (detail 1).
4. Connect the cables from the FRITZ!Box to the connectors.
5. Optional: use the zip tie to hold the cables together.
6. Place your FB-Rack in your 19 inch rack.
7. Place the Rackmount.IT front plate BELOW the FB-Rack in your 19 inch rack. Together they are 2U high.



Detail 1

Please ensure proper ventilation according to the network appliance manufacturer guidelines.

## PACKAGE CONTENTS

| Qty | Description |
|---|---|
| 1 | FB-Rack + RJ45 couplers / USB / RJ12 coupler |
| 1 | Rackmount.IT front plate |
| 2 | Zip tie |
| 7 | Cables - 0.5 meter |

**Consider the environment, recycle where applicable.**

Rackmount.IT rack mount kits are RoHS compliant, developed & manufactured in the Netherlands and made of first quality parts.

In case of problems please contact your reseller or sales@rackmount.it.

*Revision 2 - 30-07-2021*


EMEA Office
Nonnenveld 27
4811 HN Breda
The Netherlands
T +31 76 200 37 40
E sales@rackmount.it
WWW.RACKMOUNT.IT

US Office
9201 Metric Blvd - Unit A
Austin - TX 78758
United States
T +1 512 521 03 33
E sales-us@rackmount.it


RACKMOUNT.IT