HAVIT

M69 STRONG BASS
WIRELESS SPEAKER

PRODUCT MANUAL

Packing list

Bluetooth speaker x1

TYPE-C
Charging Cable x1

Dual 3.5mm audio cable x1

User manual x 1

Certificate of quality x1

Product structure



1.Power switch
2.Mode button
3.PREVIOUS/VOL−
4.Play/Pause button
5.NEXT/VOL+
6.Voice button
7.Type −C charging port
8.Micro SD card port
9.AUX in

Power ON/OFF
1.Long press the power switch for 2 seconds to turn on, the LED indicator turns blue and then flashes blue.
2.Long press the power switch for 2 seconds to turn off, the LED status indicator goes off.

Bluetooth connection
1.Turn on the Bluetooth speaker, the LED indicator flashes blue continuously while waiting for paring.
2.Then active the Bluetooth of your phone and search for "HAVIT M69". Click manually to connect. If the connection is successful, the LED indicator will turn steady blue.
3. Since the speaker can automatically reconnect to the last paired device. When the Bluetooth of your device turns on, (Just turn on the speaker), it will automatically reconnect.

Answer incoming calls
Press the play/pause button to answer incoming calls.
Tip: Since some mobile phones default to

answer calls via their own receiver, please refer to the instructions of your phone and set on your phone.

End the call
Press the play/pause button once to end the current call.

Refuse incoming calls
Long press the play/pause button for 2s to reject when there comes a call.

Last number redial
Dual press the play/pause button to redial the last calling number.

Bluetooth disconnection
Dual press the mode button to cut off the Bluetooth connection.

Mode switching
Short press mode button to select mode. (Bluetooth/Micro SD card/AUX in)

Micro SD card mode
Insert a micro SD card, the speaker will automatically recognize (with a voice prompt) and automatically broadcasts MP3

format music in it. (The Max storage of the micro SD card is 32GB).

AUX mode
Connecting your music player/phone to the speaker via the provided dual 3.5mm audio cable, then the speaker will automatically recognize.

One key for Siri
Short press the voice button to activate voice assistant.

Music playing
1. Short press the play/pause button to pause/play;
2. Long press the "−" for PREV;
3. Long press the "+" for NEXT.
4. Short press the "−" for VOL−;
5. Short press the "+" for VOL+.

True Wireless Stereo (TWS) Fit for two M69 speakers
You can connect two M69 speakers as a pair for stronger stereo and surrounding effect.
1. Make sure the Bluetooth function is OFF

on your Bluetooth player;
2. Turn on two speakers;
3. Long press mode button on either speaker for 2 seconds, then there comes up a melody which means the two speakers are now in TWS pairing status. Until LED of the auxiliary channel speaker lights up steady blue and the LED of the main channel speaker flashes, the TWS connection is successful.
4. Then active the Bluetooth of your phone and search for "HAVIT M69". Click manually to connect.

Charging
1.As product has built-in non-removable and rechargeable battery, please use the provided TYPE-C cable to charge.
2. Charging voltage and current is 5V/2.4A, please charge the speaker with the input power below 5V/2.4A.
3. Please choose the charger that is certified by the regular manufacturer.
4. The battery performance may decrease as repeating charging and using the speaker. It's a normal phenomenon for all rechargeable batteries.

5. Charge if the power LED indicator lights up red, and it goes off upon charging finished.

Specification:
Bluetooth version: V5.3
Rated power: 8W*2
Peak power: 12W*2
Battery capacity: 3.7V/3600mAh
Play time: 25H
Talk time: 25H
Charging time: 4H
Voice chat: Supported
Support: Bluetooth ,AUX ,Micro SD,TWS
Material: ABS+Fabric
Charge means: Type-C
Product size: 195*75*73mm
Net weight: 490g
Wireless working range: 18M (without obstacles)
Speaker: 48mm*2
Input voltage: DC5V/2.4A

Warnings:
1. Please follow the instruction to operate.

2. PLS charge the product with input power below 5V/2.4A, in order to protect the battery;
3. Please store or use the product in a normal temperature environment.
4. Please keep the product from heat source, such as radiators, hot air regulators, stoves, or other heat generating instruments. As it is not anti-high temperature.
5. Don't jam the ports of the product, such as charger port, LED port and microphone etc..
6. In order to protect your hearing and extend the speaker service life, it is not recommended to adjust the volume to the maximum level for a long time.
7. If the speaker system halted, long press the MFB to reset and power off.
8. Whatever reasons damage the product, please feel free to contact our after-sales staff in time rather than repair by yourself. Otherwise, you will accept without after-sales service.