

LogiLink®



Media Converter For Gigabit/2.5G/10G

Art. No.: NMC001
NMC002
NMC003

LogiLink standalone Media Converter can expand the existing Gigabit Ethernet networks with fiber optic signals without renewing entire network infrastructure.

Features:

- » Compact metal housing with double-sided ventilation
- » Ports: 1x RJ45, 1x SFP
- » LED indicators provide an easy way to monitor network activity
- » Support Auto MDI/MDI-X and auto recognition of full and half duplex
- » Automatic address learning and address aging
- » Use single-mode SFP or multi-mode SFP
- » External power supply



Art-No.	Ethernet Connection Speed	EAN Code
NMC001	1 Gbps	4052792075564
NMC002	2.5 Gbps	4052792075571
NMC003	10 Gbps	4052792075588



Specifications:

Art. No.		NMC001	NMC002	NMC003
Product		Gigabit SFP Media Converter	2.5G SFP Media Converter	10G SFP+ Media Converter
Standard		IEEE802.3, IEEE802.3i, IEEE 802.3u, IEEE802.3ab, IEEE802.3z, IEEE802.3x, IEEE802.3az	IEEE 802.3u, IEEE 802.3ab, IEEE 802.3bz, IEEE 802.3x	IEEE 802.3, IEEE 802.3u, IEEE 802.3ab, IEEE 802.3bz, IEEE 802.3an, IEEE 802.3ae, IEEE 802.3x
Interface	Copper Interface	1x 10/100/1000 Mbps RJ45 port, Auto MDI/MDI-X, auto negotiation	1x 2.5G/1G/100M RJ45, auto MDI/MDI-X, auto negotiation	1x 10G/5G/2.5G/1G/100M/10M RJ45, auto MDI/MDI-X, auto negotiation
	Fiber Optic Interface	1x 1000 Mbps SFP port	1 x 2.5GBASE-X SFP	1 x 10BASE-X SFP+
LED	LED PWR	On: Power on, Off: Power off		
	SFP Link/Act	On: There is a valid link for SFP Port Off: There is no valid link for SFP Port Flashing: SFP Port is transmitting or receiving data		
	RJ45 Link/Act	On: There is a valid link for RJ45 Port Off: There is no valid link for RJ45 Port Flashing: RJ45 Port is transmitting or receiving data		
Transmission Media		SFP Fiber, RJ45		
Enclosure		Compact-sized metal case		
Installation		Desktop, media convert chassis installation		
Dimensions		93.5 x 70.5 x 26 mm		
Weight		124 g		
Operating Temperature		0–55°C		
Operating Humidity		20-80% RH (non-condensing)		
External Power Supply		5 V DC, 0.55 A max.	5 V DC, 1 A max.	12 V DC, 1 A max.
Max. Power Consumption		1.65 W max.	2 W max.	3 W max.
Compatible LogiLink Transceivers		SFP001–SFP004	SFP005, SFP006	SFP007, SFP008

Package Contents:

- » 1x SFP Media Converter
- » 1x Power Adapter
- » 1x User Manual

Package Information:

Art-No.	Packing Dimension	Packing Weight	Carton Dimension	Carton Q'ty	Carton Weight
NMC001	103 x 80 x 60 mm	0.216 kg	440 x 230 x 690 mm	40 pcs	10.2 kg
NMC002	103 x 80 x 60 mm	0.244 kg	440 x 230 x 690 mm	40 pcs	10.2 kg
NMC003	103 x 80 x 60 mm	0.249 kg	440 x 230 x 690 mm	40 pcs	10.2 kg



*The specifications and pictures are subject to change without prior notice.

*All trade names referenced are the registered trademarks of their respective owners.