Product Line

FORTIRACK

Type

RM-FR-T15
RM-FR-T15i

Supported Models **FORTIGATE 80F FORTIGATE 81F**

DIMENSIONS	1U
COLOR	RAL 9003 White
PACKING DIMENSIONS	80 x 520 x 270 mm 3.14 x 20.47 x 10.63 in
PRODUCT DIMENSIONS (height x width x depth)	44 x 482 x 217 mm 1.73 x 18.98 x 8.54 in



MOUNTING INSTRUCTIONS

1. Place up to 2 power supplies on the rack and tie them down with 2 zip ties each.
2. Remove the 4 rubber feet from the bottom of the FortiGate.
3. Place your FortiGate on the rack & fix the FortiGate with the 2 bolts on the bottom and tighten them lightly.
4. Tie the excess length of the power cable(s) down with a zip tie(s).
5. Connect the cables from your FortiGate to the connectors.
6. Optional: use fiber patch cables (not supplied) to connect the SFP ports with fiber keystones.
7. Optional: use two zip ties to hold the cables together.
8. Place your FortiRack in your 19 inch rack.

Please ensure proper ventilation according to the network appliance manufacturer guidelines.

PACKAGE CONTENTS

Qty	Description
1	FortiRack + RJ45 / Fiber / USB coupler
8	Zip ties
2	Bolts M3x6mm
12	Cables - 0.5 meter

Fiber patch cable is not supplied due to the variety of fiber patch cables
Industrial version is supplied with shielded couplers and cables

Consider the environment, recycle where applicable.

Rackmount.IT rack mount kits are RoHS compliant, developed & manufactured in the Netherlands and made of first quality parts.

In case of problems please contact your reseller or sales@rackmount.it.

Revision 3 - 08-12-2020

EMEA Office
Nonnenveld 27
4811 HN Breda
The Netherlands
T +31 76 200 37 40
E sales@rackmount.it
WWW.RACKMOUNT.IT

US Office
9201 Metric Blvd - Unit A
Austin - TX 78758
United States
T +1 512 521 03 33
E sales-us@rackmount.it

RACKMOUNT.IT