Delock PCI Express 4.0 x16 Card to 4 x SFF-8639 NVMe - Bifurcation - Low Profile Form Factor

Description

This PCI Express card by Delock expands the PC by**four SFF-8639 interfaces**. SSDs with e.g. U.2 interface can be connected to these ports.

PCIe Bifurcation
The card requires the PCIe bifurcation of the motherboard to split the PCIe signal in order to use multiple ports.



Note

Without PCIe bifurcation only the first SFF-8639 port of the card can be used.

Specification

• Connectors:
PCIe card:
1 x PCI Express x16, V4.0
2 x SFF-8654 8i female
Connection cables:
1 x SFF-8654 8i male
1 x Molex 4 pin power plug >
2 x SFF-8639 female
• Data transfer rate up to 64 Gbps
• Supports NVM Express (NVMe)
• Bootable, ex UEFI version 2.3.1
• Supports S.M.A.R.T.
• Supports TRIM
• 4 x LED indicator
• Humidity: 15 ~ 90 %
• Operating temperature: 5 °C ~ 50 °C
• Storage temperature: -25 °C ~ 70 °C

System requirements

• Linux Kernel 4.6.4 or above
• Windows Server 2016
• Windows 7/7-64/8.1/8.1-64/10/10-64
• PC with one free PCI Express x16 / x32 slot

Package content

• PCI Express card
• Low profile bracket
• 2 x Cable SFF-8654 8i male to 2 x SFF-8639 receptacle, length ca. 80 cm
• User manual

Item no. 90077


EAN: 4043619900770

Country of origin: China

Package: Box

© 2022 by Delock. All names and symbols mentioned here are property of the respective producer. Printing errors, changes and errors excepted.

Images











© 2022 by Delock. All names and symbols mentioned here are property of the respective producer. Printing errors, changes and errors excepted.

General	
Function:	Bootable, ex UEFI 2.3.1
Supported operating system:	Linux Kernel 4.6.4 or above
	Windows 10 32-bit
	Windows 10 64-bit
	Windows 8.1 32-bit
	Windows 8.1 64-bit
	Windows Server 2016
LED indicator:	4 x
Interface	
Connector 1:	1 x PCI Express x16, V4.0
Connector 2:	4 x SFF-8639 female
connector 3:	2 x Molex 4 pin power plug

© 2022 by Delock. All names and symbols mentioned here are property of the respective producer. Printing errors, changes and errors excepted.