

2-Port DisplayPort KVM Switch

DP 1.2 Single-Display Connections, 4K@60Hz, USB Connections, 3.5 mm Audio and Mic Connections, USB 2.0 Hub, Black

Part No.: 153546

EAN-13: 0766623153546 | UPC: 766623153546

DisplayPort KVM Switch with 2 ports – Easy access and control in 4K UHD

The Manhattan 2-Port DisplayPort KVM Switch is a compact solution for providing access and control over two DP/USB-equipped computers from a single keyboard, mouse and monitor. It helps save you time on installation with its included combo cables — there's no need to purchase additional ones — that easily connect directly to the system.

Easy to use for improved efficiency

This KVM Switch helps you access your systems more efficiently without the expense and clutter of extra keyboards, mice, and monitors. You select your connected computers and audio/mic channels through the front-panel push-buttons or keyboard hotkeys. The enhanced control this KVM switch provides is ideal for high graphical content in applications like video editing, digital signage server control, medical imaging, multimedia design or dual system control workstations.

4K resolution at 60 Hz and full audio support

The ever-growing demand for higher video quality and the evolution of DisplayPort technology has put 4K-enabled computers and displays in many visually ambitious workplace and commercial applications. Supporting up to 3840 x 2160 (4K) resolution at smooth 60 Hz, this KVM Switch is right at home in your Ultra-High-Definition-equipped setup. Use an MST adapter (available from Manhattan) to connect a second monitor for maximized viewing. You also get full audio compatibility, with support for digital audio and separate analog

For more information on Manhattan products, consult your local dealer or visit www.manhattan-products.com.
All names of products or services mentioned herein are trademarks or registered trademarks of their respective owners. Distribution and reproduction of this document, and use and disclosure of the contents herein, are prohibited unless specifically authorized.

3.5 mm stereo audio jacks for microphones and speakers or headphones.

Additional USB hub port

The integrated USB 2.0 hub offers a front-facing USB-A port in addition to keyboard and mouse ports. This hub port works among your attached computers as if it were directly connected to your host computer so you can avoid having to constantly plug/unplug devices such as printers, storage drives or scanners.

Compatible with Windows®, Mac®, Linux® and more

Being OS independent, this DP KVM switch not only supports Windows, Mac OS and Linux, but it is also compatible with Unix® and even Novell® NetWare to fully support older legacy hardware.

Features:

- Controls two DisplayPort and USB-A equipped computers from a single keyboard, mouse and monitor
- Full stereo audio support through 3.5 mm speaker and microphone connections
- Switching via front-panel push buttons or keyboard hot keys
- Resolutions up to Ultra-High-Definition (UHD) 4K@60Hz (3840 × 2160)
- MST passthrough to connect multiple monitors via a single DP port using an MST adapter (available from Manhattan)
- Additional USB 2.0 type-A hub port to connect storage drives, printers, scanners and more
- Digital audio support through DisplayPort 1.2
- Ideal for hi-res digital signage server control, medical imaging, multimedia design and more
- Supports Windows®, Mac OS®, Linux®, Unix® and Novell®
- True Transparent USB (TTU) emulation technology supports most keyboard and mouse designs
- HDCP 1.4 compliant
- BIOS-level hardware installation; no drivers or control software required
- Two 1.8 m (6 ft.) DisplayPort/USB-B/Audio to USB-A combo connection cables included
- Compact desktop format with rugged metal housing
- USB powered; use optional 9 V / 300 mA power supply (not included) if your setup delivers insufficient power input
- Three-year warranty

For more information on Manhattan products, consult your local dealer or visit www.manhattan-products.com.
All names of products or services mentioned herein are trademarks or registered trademarks of their respective owners. Distribution and reproduction of this document, and use and disclosure of the contents herein, are prohibited unless specifically authorized.

Specifications:

Standards and Certifications
• CE
• RoHS
• FCC

Connections
• Console ports
  - 1 x DisplayPort female 20-pin
  - 2 x USB-A female 4-pin
  - 1 x 3.5 mm stereo audio microphone female
  - 1 x 3.5 mm stereo audio speaker female
• Computer/host ports
  - 2 x DisplayPort female 20-pin
  - 2 x USB-B female 4-pin
  - 2 x 3.5 mm stereo audio microphone/speaker female combo port
• Other
  - 1 x USB-A female 4-pin
  - 1 x 9.0 V DC/0.3 A power jack

LEDs
• 2 x red (online)
• 2 x green (selected)

Supported Operating Systems
• Windows 2000/2003/XP/Vista/7/8/8.1/10
• Apple Mac OS 9.0 to 10.6 (Snow Leopard)
• Linux RedHat 9.0 or higher/SuSe 10 or higher/Debian 3.1/4.0/Ubuntu 7.04/7.10
• UNIX AIX 4.3 or higher/FreeBSD 5.5 or higher/Sun Solaris 8 or higher
• Novell Netware 6.0 or higher

Physical
• Dimensions (L x W x H): 132 x 92 x 66 mm (5.2 x 3.62 x 2.6 in.)
• Weight: 600 g (1.32 lbs.)
• Housing: metal

Operating Environment
• Operation temperature: 0 - 50°C (32 - 122°F)
• Storage temperature: -20 - 60°C (-4 - 140°F)
• Humidity (noncondensing): 0 - 80%

Package Contents
• 2-Port DisplayPort KVM Switch
• Two 1.8 m (6 ft.) DisplayPort/USB-B/Audio to USB-A combo connection cables included

For more information on Manhattan products, consult your local dealer or visit www.manhattan-products.com.
All names of products or services mentioned herein are trademarks or registered trademarks of their respective owners. Distribution and reproduction of this document, and use and disclosure of the contents herein, are prohibited unless specifically authorized.

Please note: Mac® computers can only be controlled with a standard PC mouse and keyboard, not with Mac peripherals.

This product is part of a group; the complete list of variations follows:
- #153522 - 2-Port Dual-Monitor HDMI KVM Switch
- #153539 - 4-Port Dual-Monitor HDMI KVM Switch
- #153546 - 2-Port DisplayPort KVM Switch













For more information on Manhattan products, consult your local dealer or visit www.manhattan-products.com.
All names of products or services mentioned herein are trademarks or registered trademarks of their respective owners. Distribution and reproduction of this document, and use and disclosure of the contents herein, are prohibited unless specifically authorized.